

GUITAR/BASS/KEYBOARD AMPS



AL-610 – GUITAR AMPLIFIER
POWER: 10 WATTS, 6.5" SPEAKER,
VOLUME, TONE CONTROLS,
INPUT, HEADPHONE JACK



AL-615 AMP
15 WATTS R.M.S WITH OVERDRIVE!!!



AL-625 – GUITAR AMPLIFIER
POWER: 25 WATTS, 8" SPEAKER, OVERDRIVE,
VOLUME, TONE, AND BASS CONTROLS, INPUT,
HEADPHONE JACK



AL-640
2 X 8" SPEAKERS, 40 WATTS R.M.S. OVERDRIVE ,CHO-
RUS /ECHO/ REVERB. THIS BABY ROCKS!!!



ELECA I-POD E-AMP
COMBINES A PRACTICE AMP WITH AN IPOD INTERFACE, PLUG IN
YOUR GUITAR AND YOUR IPOD AND PLAY ALONG WITH YOUR
FAVORITE BANDS, STEREO 15W AMP WITH A 7" WOOFER IN EACH
CABINET, SEPARATE CONTROLS FOR IPOD AND GUITAR, MINI
JACK FOR CD PLAYER INPUT, HEADPHONE OUT, COMES WITH
PADDED CARRYING CASE



EB-200 – BASS AMPLIFIER
POWER: 20 WATTS, 9" SPEAKER,
VOLUME, PRESENCE, 3 BAND EQ



PIGNOSE AMP
SMALL POWERFULL AMP THAT CAN BE
PLUGGED IN THE WALL OR RUN ON
BATTERIES, CLASSIC DESIGN, POWER
SUPPLY INCLUDED!



KARERA GT-1000
9 VOLT BATTERY POWERED PRACTICE AMP WITH VOL-
UME, TONE AND OVERDRIVE, ALSO HAS HEADPHONE OUT,
AC ADAPTER PLUG IN, AND BELT CLIP.